

# SINGLE DOOR ALARM 100 SERIES


## Custom Models To Meet Specific End-User Needs




### AVAILABLE MODELS INCLUDE:

- **SDA-101**  
Basic Model, No Strobe
- **SDA-103**  
Includes Strobe
- **SDA-104**  
Includes Strobe & Timer To Stop Alarm After 30 Seconds
- **SDA-105**  
Includes Strobe & Output To Remote Alarm Panel
- **SDA-12\_**  
Substitues 85db Siren For 110db Siren

### SDA-103



**Alarm Power Supply, Siren & Strobe With Battery Back-Up**  
 Width: 7-1/2"  
 Height  
 Box: 8-1/4"  
 Strobe: 2"  
 Total: 10-1/4"  
 Depth: 3-1/2"



**Key Switch Box**  
 Width: 2-7/8"  
 Height: 4-1/2"  
 Depth: 2-1/8"  
 Mortise Cylinder Required (by others)

Surface Mounted Alarm Contacts (NC) are also furnished. If the mounting wall for the Alarm Power Supply (APS) is drywall, we recommend running the alarm contact wire within the drywall and entering the APS through the rear.

110vAC is required for direct connection into the Alarm Power Supply

The armored cable is shipped connected to the Key Switch Box. Approx. 48" of cable is provided. It is field installed to the terminal strip within the Alarm Power Supply Unit.

### SDA-104

Identical to SDA-103, except alarm shuts off and resets after 30 seconds.

### SDA-105

Identical to SDA-103 with additional alarm output (12vDC) to alarm panel and additional input (N.O.) for reset from alarm panel.

### SDA-105A

Identical to SDA-103 with additional output (N.O.) to alarm panel and additional input (N.O.) for reset from alarm panel.

### SDA-103-DPA

Identical to SDA-103 with field adjustable door-prop alarm. Alarm is shunted by use of card reader. If door remains continuously open for 20 seconds, alarm will sound until reset. Time frame (20 seconds) is field adjustable.

### SDA-101

Identical to SDA-103, except does not include strobe